

© 2014 Tyco Electronics Corporation. All rights reserved.

=	Connectivity		CUSTOMER DRAWING Raychem Adapters			HEXASHIELD ADAPTER FOR ARINC 600 SS 3 CONNECTOR FOR HEX40YY- 17-AY-3 AND HEX40YY-19-AY-3 ADAPTERS					
DIMENSIONS A	RWISE SPECIFIED RE IN MILLIMETERS. DNS ARE SHOWN IN	Tyco Electronics reserves the rightime. Users should evaluate the sapplication.	HEXA6KIT-00100								
DRAWN: NSWATKO	DATE: 02/24/2014	APPROVED: IMYONG 04/25/2014	RELEASED PER ECO-14-006409	CAGE CODE: 06090	REV: A	SCALE: NONE	SHEET: 1 OF 2				

KIT DESCRIPTION

ITEM	QTY	DESCRIPTION	MATERIAL
1	1	BACKSHELL ASSEMBLY	ALUMINUM ALLOY
	17	CHEESE HEAD SCREW Ø 4-40 UNC x 1/4" LONG	STAINLESS STEEL - PASSIVATED
	6	CHEESE HEAD SCREW Ø 6-32 UNC x 7/16" LONG	STAINLESS STEEL - PASSIVATED
	6	WASHER Ø 6-32 UNC	STAINLESS STEEL - PASSIVATED
2	2	HEXASHIELD BANDSTRAP ADAPTER ASSEMBLY- A7	ALUMINUM ALLOY
3	4	HEXASHIELD BANDSTRAP ADAPTER ASSEMBLY – A8	ALUMINUM ALLOY
4	46	HEX02 FERRULE (NOT SHOWN)	COPPER ALLOY
5	46	OUTER SLEEVE (NOT SHOWN)	FLUOROPOLYMER (PVDF)
6	46	INSULATION SLEEVE (NOT SHOWN)	FLUOROPOLYMER (PVDF)

APPLICATION

- This adaptor assembly is designed to be mounted on the following connector: ARINC 600 Shell Size 3
- It includes 2 x HEX40-YY-YY-17-AY-3 and 4 x HEX40-YY-YY-19-A7-3 adapters.

INSTALLATION

- See Installation Procedures RPIP-696-02 and -04 for basic instructions.

PACKAGING

- All assemblies are supplied in a plastic bag.

NOTES

- 1. Assembly is to be permanently marked with Code Identity Number and Part Number. (e.g. 06090 HEXA6KIT-00100)
- 2. Individual parts are to be permanently marked with Code Identity Number and Part Number. (e.g. 006090 HEX40AB-00-21-A9-3)

CUSTOMER DRAWING		ا NG	HEXA6KIT-00100							
Ra	ychem Adapte	ers								
DRAWN: NSWATKO	DATE: 02/24/2014		OVED: ONG 04/24/	2014	RELEASED PER ECO-14-006409	CAGE CODE: 06090	REV: A	RPN: CV5867-000	SCALE: NONE	SHEET: 2 OF 2